

# MIRRORSTONE

LIGHTING SPECIALIST

## 4 zone RGB+CCT remote

Model No.:MS-EZI-C5

### Product Feature

- 2.4GHz wireless transmitting technology , fast transmitting, stable signal and anti-interference
- Control multi devices at the same time
- Dim color, brightness and mode
- Change color and speed of dynamic mode
- Working with multi controllers ( control distance 30m)
- simple magnetic installation
- Control lighting scene freely , for commerical and home lighting scene




### Product Parameter

Product Name: :	4 zone RGB+CCT remote	Working temperature :	-10~40°C
Model No.::	C5	EMC standard(EMC):	ETSI EN 301 489-1 V2.2.3 ETSI EN 301 489-3 V2.3.2
Working voltage:	3V(AAA*2PCS)	Security Standard (LVD) :	EN 61347-2-11:2001+A1:2019 EN 61347-1:2015+A1:2021 EN 62493:2015+A1:2022
Standby consumption:	15μA	Radio equipment (RED) :	ETSI EN 300 400 V2.2.1
Transmission:	6dBm	Certification:	CE、EMC、LVD、RED
Protocol:	2.4GHz RF		
Modulation:	GFSK		
Control Distance:	30M		

Remote



Remote Holder



## Function



### Function

White: 

For white color

Dynamic Mode: 

Press continuously to change different mode

RGB Ring: 



Group ON (Link/Unlink):

For different zones



Brightness slider: 



## Multi Function:

Speed-/ CCT-/ Saturation+



For dynamic mode, speed-

For white mode, CCT-

For RGB mode, saturation+

## Multi Function:

Speed+/ CCT+/ Saturation-



For dynamic mode, speed+


For white mode, CCT+

For RGB mode, saturation-

## Link/Unlink

### Link


controller must link with remote before using it



turn off light 10 seconds and  
turn on again



short press "ON" 3 times within 3  
seconds




link is done once light flashes 3  
times slowly



Link is failed if light doesn't flash, please repeat above steps  
(Attention: can not link again if remote already finished linking)


### Unlink



turn off light 10 seconds  
and turn on again



short press "ON" 5 times within 3  
seconds




link is done once light flashes  
10 times quickly



Unlink is failed if light doesn't flash, please repeat above steps  
(Attention: no need to unlink if the light never be linked)

## Installation



Remove the sticker on the holder



Stick the holder on the wall and put remote on the holder

## Attention:

1. Don't use it in humidity or high temperature area, please take out battery if don't use it frequently and keep it in dry or static electricity area
2. Don't use it near metal or strong magnetic area, it will affect signal and lost distance.